Nomad

2

SERVICE BULLETIN

SUBJECT: RETRACT SAFETY MICROSWITCH REPLACEMENT (MODIFICATION N366)

1. Planning Information

A. Effectivity

(1) Aircraft Affected

All Nomad N22-Series and N24-Series aircraft whose log books do not already record the embodiment of Mod N366 of compliance with Service Bulletin NMD-32-12.

Pre-certification implementation of the intent of this service bulletin is recorded in the airframe log book as Mod N366.

(2) Spares Affected

Nil.

B. Reason

The existing retract safety microswitch is replaced by an hermetically-sealed microswitch to prevent the ingress of moisture and dirt.

C. Description

A new microswitch and mounting bracket is fitted to the LH main gear oleo leg upper torque link assembly and a new terminal board fitted to the LH wheel pod wall.

D. Compliance

The incorporation of this modification is recommended.

E. Approval

The modification detailed herein has been approved pursuant to Air Navigation Regulation 40 and conforms with the type certification requirements.

F. Manpower

Three manhours.

G. Material-Price and Availability

The parts required to incorporate the modification detailed in this Service Bulletin are available as Kit No. NMD-32-12-1 from the operator's local distributor. Distributors are to place a purchase order on G.A.F. through the normal procurement procedure. Purchase orders are to quote the aircraft Serial No. and Service Bulletin No. NMD-32-12. This Kit will be available ex-factory from October, 1981 at \$A634 each. The price remains effective for 90 days from the date of this Bulletin.

H. Tooling-Price and Availability

None required.

J. Weight and Balance

Negligible effect.

K. References

MM - Maintenance Manual.

L. Publications Affected

Maintenance Manual Illustrated Parts Catalogue Wiring Diagrams Manual.

2. Accomplishment Instructions

- A. Jack up aircraft until oleo legs are fully extended and the wheels clear of ground (Ref MM 7-00-00) and remove outer LH wheel (Ref MM 32-40-51).
- B. Ensure that all electrical power is switched off.
- C. Remove cable assembly P/N 1/N-81-343
 - (1) Remove and discard the microswitch P/N 5750 and attaching parts.
 - (2) Remove and discard tiedown straps P/N MS 3367-5-9 securing cable assembly to hydraulic brake pipe on the LH main gear oleo leg. Note position of tiedown straps.
 - (3) Disconnect cable assembly from terminal board TB21 on the wheel pod wall (Ref Figure 1).
- D. Remove and discard terminal board TB21 P/N MS27212-1-4 and the self-locking nuts P/N MS21083-D04 but retain the screws P/N MS35206-216.

- E. Fit new terminal board TB53 P/N MS27212-1-6.
 - (1) Remove TB number and terminal idents from the wheel pod wall.
 - (2) Locate the position of the forward fixing hole for the new terminal board (Ref Figure 2) and drill a 3.0 mm dia hole in this position.
 - (3) Secure the new terminal board using the screws P/N MS35206-216, retained in Para 2.C. and new self-locking nuts P/N MS21083-D04.
 - (4) Paint the TB number and terminal idents in black characters 0.125 inches high on the wheel pod wall in the positions shown in Figure 2.
- F. Remove brackets P/N 1/N-40-648 and P/N 1/N-40-649 from upper torque link assembly of LH main gear oleo leg.
 - (1) Drill out rivets P/N MS20470AD4-6 securing bracket P/N 1/N-40-649 and remove and discard bracket.
 - (2) Remove and discard bracket P/N 1/N-40-648 and attaching parts, screws P/N MS35206-229, self-locking nuts P/N MS21083-N06 and washers P/N AN960-PD6.
- G. Secure bracket P/N 1/N-40-934 to the upper torque link using screws P/N MS35206-217, washers P/N AN960-4 and self-locking nuts P/N MS21083 NO4.
- H. Fit new retract safety switch assembly P/N 1/N-81-694.
 - (1) Secure microswitch to bracket P/N 1/N-40-934.
 - (2) Secure cable loom to hydraulic brake pipe on main gear oleo leg using tiedown straps P/N MS3367-5-9.
 - (3) Locate the tiedown straps in the positions noted in Para 2.C.(2).
 - (4) Connect the cable conductors to terminal board TB53 on the wheel pod wall as shown in Figure 3.
 - (5) Refit the outer LH wheel (Ref MM 32-40-51).
- H. Adjust retract safety microswitch.
 - (1) Ensure LH main gear oleo leg is fully extended.
 - (2) Connect a continuity tester across terminals 1 and 2 of terminal block TB53.

Page 3 of 7

- (3) With microswitch actuating plunger in contact with the oleo leg adjust microswitch position until continuity is obtained across terminals 1 and 2.
- (4) Further adjust switch position until actuating plunger has an override of 0.030 inches after continuity occurs between terminals 1 and 2, tighten switch mounting locknut.
- (5) Slowly lower aircraft to ground and check that an open circuit is obtained across terminals 1 and 2 just before contact is broken between the microswitch actuating plunger and the oleo leg.
- (6) Disconnect continuity tester from terminals 1 and 2 of terminal block TB53.
- (7) Move jacking equipment clear of aircraft (Ref MM 7-00-00).

3. Material Information

A. Parts Required per Aircraft

- (1) One kit P/N NMD-32-12-1 is required for each aircraft.
- (2) Each kit P/N NMD-32-12-1 comprises the following items:

<pre>Item P/N</pre>	<u>Title</u>	Qty
MS27212-1-6	Terminal board assembly	1
MS21083-D04	Nut, self-locking	2
1/N-40-934	Bracket ·	1
MS35206-217	Screw	4
AN960-4	Washer, flat	4
MS21083-N04	Nut, self-locking	4
1/N-81-694	Retract safety switch assembly	1
MS3367-5-9	Strap, tiedown	5

B. Parts Modified and Re-identified by the Operator

None.

C. Parts Required to Modify Spares

None.

D. Removed parts


<pre>Item P/N</pre>	<u>Title</u>	Qty	Recommended Disposition
1/N-81-343	Cable assembly	1	Scrap
5750	Microswitch	1	Scrap
MS3367-5-9	Strap, tiedown	5	Scrap
MS21083-D04	Nut, self-locking	2	Scrap
MS27212-1-4	Terminal board assembly	1	Scrap
1/N-40-649	Bracket	1	Scrap
1/N-40-648	Bracket	1	Scrap
MS21083-N06	Nut, self-locking	2	Scrap
AN960-PD6	Washer, flat	2	Scrap
MS35206-229	Screw	2	Scrap

E. Special Tools and Equipment Required


None.

4. Recording Action


Record compliance with S/B NMD-32-12 in the airframe log book



Installation of Landing Gear Retract Safety Switch Assembly Figure I



Installation of TB53 in LH Wheel Pod Figure 2



Connections to TB 53 Figure 3